

MAE143 B - Linear Control - Winter 2021
Midterm #1, January 26th

Instructions:

1. You have from 9:30AM to 10:50AM to finish this exam.
2. You have until 11:00AM to submit your answers on gradescope.
3. The exam is to be done individually.
4. All answers should be manuscript.
5. No typed answers of any form will be accepted.
6. All graphs and diagrams have to be sketched by hand. Include enough detail.
7. If you use a tablet to do the work make sure it is handwritten.
8. This exam has 4 questions, for a total of 21 points.

Questions:

1. (3 points) **Stabilization**

A system with transfer-function

$$G(s) = \frac{s}{s-1}$$

is to be stabilized using a standard feedback controller. Of the following controllers, which one would be the best choice:

- a) $K(s) = 1$
- b) $K(s) = -2$
- c) $K(s) = 2/s$

Explain your reasoning.

For the remaining questions consider the following system:

The temperature of a substance in a container left at constant ambient temperature, T_a , with a heat source, q , can be modeled as

$$mc\dot{T}(t) = \frac{1}{R}(T_a - T(t)) + q(t), \quad (1)$$

in which m and c are the substance's mass and specific heat, and R is the overall system's thermal resistance.

2. Modeling and Open-Loop Response

- (a) (2 points) Calculate the transfer-function $G(s)$ from q to T and draw a block diagram showing the relationship between G and the signals $q(t)$, $T(t)$, and $w(t) = T_a/R$.
- (b) (2 points) Show that when $q(t) = \bar{q}$ is constant and the initial temperature is T_0 then

$$T(t) = T_a + (T_0 - T_a)e^{-t/mcR} + R\bar{q}\left(1 - e^{-t/mcR}\right). \quad (3)$$

Sketch the solution assuming that $T_0 = T_a$ and $\bar{q} > 0$.

HINT: You do not have to "derive" the solution if you can quote the book or the lecture notes.

- (c) (2 points) A student performed the following experiment. The heat source was turned on until 5 kg of a substance with specific heat $c = 5000$ J/kg K reached a temperature of 75° C, at which point the heat source was turned off. The time that it took for the substance's temperature to reach 50° C was 900 s. Use this information and the ambient temperature $T_a = 25^\circ$ C to estimate the parameter R .

3. Proportional Control

In this question, assume that $mc = R = 1$.

Consider the proportional control law

$$q(t) = Ke(t), \quad e(t) = \bar{T}(t) - T(t) \quad (4)$$

where $\bar{T}(t)$ is a reference temperature.

- (a) (1 point) Draw a block diagram of the corresponding closed-loop system showing the relationship between G , K and the signals $\bar{T}$, T , e , q , and w .
- (b) (2 points) Calculate the closed-loop transfer-functions from $\bar{T}$ to e and from w to e .
- (c) (1 point) What are the values of K for which the closed-loop system is asymptotically stable?
- (d) (2 points) Does the signal $T(t)$ converge to $\bar{T}$ when $\bar{T}(t) = \bar{T}$ is a constant? Explain.

4. Integral Control

In this question, assume that $mc = R = 1$.

Consider the integral control law

$$q(t) = K_i \int_0^t e(\tau) d\tau, \quad e(t) = \bar{T}(t) - T(t) \quad (5)$$

where $\bar{T}(t)$ is a reference temperature.

- (a) (2 points) Calculate the closed-loop transfer-functions from $\bar{T}$ to e and from w to e .
- (b) (2 points) What are the values of K_i for which the closed-loop system is asymptotically stable?
- (c) (2 points) Does the signal $T(t)$ converge to $\bar{T}$ when $\bar{T}(t) = \bar{T}$ is a constant? Explain.